# 71505N

## ZITON ZP3 Series, ZP3-4L, 4-loop analogue control panel, English, red

### Recognise real fires sooner

Advanced panel design combined with high sensitivity smoke and fire sensing enables the ZP3 control panel not only to identify and disregard conditions that would result in false or unwanted alarms, but to recognise real fires sooner. The ZP3 is available in  2 and 4 loop configurations, accommodating up to 508 sensing addresses. For sites requiring more loops, panels may be networked together to form systems capable of controlling more than 30.000 devices from as much as 64 control panels.

### Unique device addresses

Up to 127 line devices (detectors, call points, sounders or interface units) may be connected to each of the ZP3 loops. All loop devices incorporate switch settings enabling them to be assigned a unique address, the location of which is pinpointed and polled by the panel every two seconds. Variations in the detector's environment caused by increases of temperature or products of combustion are reported to the panel where they are processed and compared to known fire data prior to any alarm output being activated.

### Software flexibility

Constant communication between control panel and detector enables the ZP3 to provide a wide range of user facilities including pre alarm, constant sensitivity adjustment, service and near service listings for all detector types. Software flexibility enables facilities such as alarm organisation, evacuation procedures and complex cause and effect requirements to be easily programmed into any system. All customer and site data is held in non volatile flash memory, ensuring both ease of initial system data input and subsequent on site amendments and modifications should they be required.

### Optional facilities

An onboard printer module together with a series of facility boards can be added to the standard panel to extend any panel up to 768 programmable inputs and outputs.

### Remote diagnostics

Designed to provide the user with full facilities for both fault diagnosis and system configuration off site, the remote diagnostics hardware and software package makes information available to service personnel prior to visiting site for remedial action or maintenance activity.




### Details

- CPR Certified to EN54:2 and 4
- Advanced sensing techniques
- Extensive networking ability
- Loop powered sounders support
- Ease of operation
- Service and near service facility
- Sophisticated alarm verification
- Automatic self test
- Day / night control
- Radio loop interface support
- Automatic contamination adjustment for each detector
- Intelligent loop isolation
- Self test sounder support
- Password protection
- Event log

# 71505N

## ZITON ZP3 Series, ZP3-4L, 4-loop analogue control panel, English, red

## Technical specifications

### General

| | |
|---|---|
| Communication ports | Z-Port 1 Planner, RS232 Z-Port 2 Network, RS485 / fibre optic, USB port |
| Maximum system capacity (device count) | up to 130K |
| Network size (nodes) | up to 256 |

### Electrical

| | |
|---|---|
| Operating voltage | 230 VAC 50 Hz ±10%, 0.75 A<br>24 to 50 VDC |
| Current consumption | 420 mA @ 24 VDC (Quiescent, 4 loops with 0 devices)<br>820 mA @ 24 VDC (Alarm, 4 loops with 25% zones in alarm) |

### Loop

| | |
|---|---|
| Maximum loop capacity | 4 |
| Cable rating | 2 core screened (to local codes and standards) |
| Loop monitoring | Open/short circuit, earth fault, device removal, wrong device type |

### Zone

| | |
|---|---|
| Maximum zone capacity | up to 508 |
| Loop Capacity | 127 addresses |

### Standby battery

| | |
|---|---|
| Capacity | up to 28 |
| Batteries supported in housing | 2 x 12 V SLA |

### Physical

| | |
|---|---|
| Form factor | Medium |
| Physical dimensions | 540 x 410 x 137 mm (H x W x D) |
| Shipping weight | 11 kg |
| Mounting type | Recessed mount, Surface mount |
| Material | Sheet steel |

### Environmental

| | |
|---|---|
| Operating temperature | -5 to +40°C |
| Relative humidity | 10 to 90% noncondensing |
| IP rating | IP30 (indoor use only) |

### Switched outputs (standard)

| | |
|---|---|
| Sounder circuits | 2 x dual (monitored & programmable) |
| Fire (common) | 1 x volt free N/O or N/C |
| Fault (common) | 1 x volt free N/O or N/C |
| Remote manned centre (fire) | 1 x monitored |
| Remote manned centre (fault) | 1 x monitored |

### Switched I/O (optional & programmable)

| | |
|---|---|
| Non loop devices | 768 max, consiting of sounder circuits, relay outputs, transistor outputs, monitoring inputs |

### Stem status indicators

| | |
|---|---|
| LEDs | 87 LEDs, text display 4 line, 160 character, LCD (back lit) |
| LCD (back lit) | 4 line, 160 character |

### Selectable features

| | |
|---|---|
| | Common sounders, coincidence alarm, RMC fire & fault, zone walk test, control output, output delays, alarm counter, sounder silence delay, alarm verification |

KIDDE COMMERCIAL

As a company of innovation, Kidde Global Solutions reserves the right to change product specifications without notice. For the latest product specifications, visit firesecurityproducts.com online or contact your sales representative.

Last updated on 14 October 2026 - 16:55