
EST-XCTRLINE-2

Loudspeaker line control card, 2 lines

Overview

EST-xCTRLN-2 provides 2 independent speaker line outputs (A, B). Card allows to switch between main and spare amplifiers. Line measurement methods can be made by: Impedance, Loop or End of Line Module (EOL).
The measurement method is selected from the software configuration. EST-xCTRLN-2 provides fault detection, opening and ground leakage.



EST-XCTRLINE-2

Loudspeaker line control card, 2 lines

Technical specifications

Electrical

Current consumption	121 mA max. for 48 V
Power supply	Internal form the Control Unit backplane
Type of connector	6 pin screw terminal type PHOENIX, 5.08 mm
Impedance measurement frequency	1 kHz to 48 kHz
Frequency of the signal for EOL modules	18 kHz to 24 kHz
Maximum measured current	20 A
Maximum measured voltage	200 V
Accuracy of measurement	up to 5%

Physical

Physical dimensions	70 x 215 x 30 mm (W x H x D)
Accessories	Screw terminals 6 pins, the distance between the partitions 5.08 mm

Environmental

Operating temperature	0 to +60°C
Storage temperature	-20 to +70°C
Relative humidity	15 to 80% noncondensing (operation) 5 to 95% noncondensing (storage)

Regulatory

Standards	EN54-16

EDWARDS
Built for Resilience

As a company of innovation, Kidde Global Solutions reserves the right to change product specifications without notice. For the latest product specifications, visit firesecurityproducts.com online or contact your sales representative.

Last updated on 3 February 2025 - 11:57